

Quick Reference Guide

CREXENDO 300G INTERNET PHONE

The Basics

How to Make a Call

1) Using Phone Handset:

- Lift Handset
- Dial the number or extension of the party you wish to reach
- Press Send Softkey or wait for call to complete and for recipient to answer

2) Using Speaker Phone:

- Lift Handset
- Dial the number or extension of the party you wish to reach
- Press Send Softkey or wait for call to complete and for recipient to answer
- Press Speaker button
- OR
- Do **not** lift Handset
- Dial the number or extension of the party you wish to reach
- Press Send Softkey or wait for call to complete and for recipient to answer

3) Using Headset:

- Press the Line button you wish to dial out on
- Dial the number or extension of the party you wish to reach
- Wait for recipient to answer

How to Answer a Call

1) Using Phone Handset:

- When phone rings, lift Handset
- Begin speaking

2) Using Speaker Phone:

- When phone rings do **not** lift Handset
- Press Speaker button
- Begin speaking

3) Using Headset:

- When phone rings, press the Answer Softkey or the flashing inbound line button
- Begin speaking

Using a Headset

Please use a headset that supports an RJ9 (Modular jack) interface for best results.

- After connecting the Headset, press the Headset button. The Headset button will light up and all incoming calls will now ring through to the Headset

1) Switching to a Headset when on a call:

- Do **not** hang up Handset
- Put on the Headset
- Press the Headset button
- Hang up the Handset

Checking Your Voicemail

1) From your phone:

- Do **not** lift Handset
- Press lighted MESSAGE button
- Lift Handset or continue to use Speaker Phone
- Enter Password (PIN)
- OR
- Lift the Handset
- Dial your Company's VM Extension
- Enter Password (PIN)

2) Using Crexendo Web Portal:

- Log into your Crexendo Web Portal
- Double-click the message to play through PC's speakers

3) From outside line:

- Dial 877-282-4524
- Enter 10-digit Direct Dial number for your phone
- Enter your ID (Extension Number)
- Enter Password (PIN)

Voicemail Message Options

1) Delete Voicemail Message:

- Press 7

2) Forward to another user's voice mailbox:

- Press 8 Key

Forward without introductory message:

- Press 8

Forward with introductory message:

- Press 1
- Record your introductory message
- Press 2 to save the message
- Enter the Extension Number where the message is to be forwarded followed by #

3) Rewind or Fast Forward an email message:

- While listening to the message:
 - **Rewind** - Press 4
 - **Fast Forward** - Press 6

The message will rewind or advance a few seconds each time you press the key.

4) "Skip" the header announcement and go directly to the message by pressing the pound (#) key.

Quick Reference Guide

CREXENDO 300G INTERNET PHONE

Options Executed on the Phone

Changing Your PIN/Password, Your Name, and Recording Your Voicemail Greeting

- Dial the Voicemail Extension (usually x4000) from your phone
- Enter your PIN (Password)
- After any new messages have played, press the 5 Key for Advanced Options

Changing your Name: Press 3 and follow the recorded directions

Changing PIN/Password: Press 6 and follow the recorded directions

Recording your Greeting: Press 1 and follow the recorded directions

Forwarding Your Phone

- Press the Menu Softkey
- Press 2 or use arrows to select Features
- Press 1 or OK to choose Call Forward
- Press 1 or OK to choose Always Forward
- Use the Arrow buttons (left/right) to enable/disable
- Press 2 or arrow down to select Forward to:
- Use keypad to enter the forwarding number or extension
- Press the Save Softkey or OK to save your changes

Activating Do Not Disturb on Your Phone

- Press the DND Softkey from the Home screen. No calls will be received

Transferring a Call – Blind Transfer

1) Transfer before answering:

- Press the Forward Softkey
- Enter the number or extension the call is to be transferred to
- Press the Send Softkey or the # key

2) Transfer after answering:

- Press the Transfer Softkey
- Enter the number or extension the call is to be transferred to
- Hang up the phone

Transferring a Call – Attended (Warm) Transfer

- Press the Transfer Softkey
- Enter the number or extension the call is to be transferred to
- When the person answers, make the introduction, then

- Hang up the phone
If no answer or the caller does not wish to be transferred to voicemail, press Cancel Softkey to return to the call

Transferring a Call Directly to Another Extension's Voicemail

- Press the Transfer Softkey
- Enter *10 plus the extension of the voice mailbox the call is to be transferred to
- Press the Transfer Softkey again

Transfer Incoming Call When already on a Call

- Press the flashing line key to place current call on hold and answer new caller; Press Transfer Softkey.
- If the call is to be transferred to another number/extension, Press 1 for New Call, then press Select, enter the number or extension and press the Transfer Softkey again
- **OR** Arrow to a listed extension if you want to join the new caller with someone already on the line; press Select. Callers will be joined and you will no longer be part of that conversation

How to Use Speaker Phone

1) Before making a call:

- Begin dialing without picking up the handset

2) During a call:

- Press the Speaker Button

What is the "RD" Button?

"RD" stands for Redial.

1) Redialing the last number dialed:

- Pick up the Handset
- Press the RD Button
OR
- Press the RD button twice if using the Speaker Phone

2) Redialing a previous number:

- Do **not** pick up the Handset
- Press the RD button to see a list of all of your recent outbound calls
- Arrow up/down in the list to select the number
- Press the Send Softkey and pick up the Handset

Conference Calling

- Dial the first party
- Once the first party has answered, press the CONF Key
- Dial the second party
- After the second party has answered, press Conf Softkey OR the CONF Key. All parties should be connected

Quick Reference Guide

CREXENDO 300G INTERNET PHONE

Adding Contacts

1) Adding a New Contact

- Press the Directory Softkey
- Press 1 or OK for Local Directory
- Press 1 or OK for Contacts
- Press the Add Softkey
- Press the abc key to select the correct character set, case (upper/lower), or letter/number combination.
- Using the keypad, enter the name of the contact, pressing the key multiple times to locate the correct character.
- Press zero (0) to create a space
- Press the down arrow to enter phone numbers
- Press Save

2) Adding a Contact from previous caller still in History

- Press the History Softkey
- Arrow up and down to select a caller
- Press the Option Softkey and select Add to Contacts
- Press OK and use keypad to enter the name
- Press Save

a) Deleting:

- Use the right/left arrows to position the flashing cursor to the right of the character(s) to be removed
- Press the Delete Softkey. (Acts as a backspace)

b) Editing

- Use the right/left arrows to position the flashing cursor in the place where characters are to be added
- Use the keypad to enter information

- Press 3 or arrow down for Remote Phonebook
- Press 1 or OK for Company Directory
- Arrow up/down in the list to select the number
- Press Dial to call

Options Executed through the Crexendo Web Portal:

www.crexendotelecom.com

How to Change Your Status

- Look for your name in the upper right corner of any screen. (The word next to your name indicates the Status.)
- Click on the Down Arrow to the right of the Status. Select a new option

How to Add a “Find Me” Status

- Click on the Status Submenu of the Phone Menu
- Add a Status named “Find Me” and select Ring Mode
- Add the number by selecting from the “Add a Number” dropdown list.

Configuring a Feature Key for Speed Dial






- Click on the Device Submenu of the Phone Menu.
- Select (double-click) your phone
- Click the Feature Key to be programmed
- If Inactive, choose Speed Dial
- Type in the phone number to be dialed each time the button is pushed

Company Directory

- Press the Directory Softkey

For assistance,
please call
855.211.2255

What do the icons on your phone mean?

	Mute function. While on mute the party you are speaking with will not hear you. To turn on/off the mute, press the “MUTE” button on/off during a call.
	This icon will flash when you have missed a call. To view call information press the View Softkey. While viewing a missed call, press Send to dial, Delete to remove from your call history, or Menu to return to your home display. When viewing Call history, this icon will not be blinking, but still indicates there was a missed call.
	You have call forwarding activated. Refer to the Forwarding Your Phone instructions above.
DND	You have activated your Do Not Disturb function. Refer to the Activating Do Not Disturb on your Phone instruction above.
	When blinking, indicates that you have a new voicemail. Refer to the Checking Your Voicemail instructions above.
	Blinking indicates there is a problem with your phone’s connection to the internet. Unplug your phone’s power and recheck all plugs and cables. Check your internet connection.